



ASUS PRO WS WRX90E-SAGE SE AMD WRX90 Socket sTR5 EEB

Brand : ASUS

Product code: 90MB1FW0-M0EAY0

Product name : PRO WS WRX90E-SAGE SE

AMD WRX90, 8 x DIMM slots, DDR5, ECC, Realtek 1Gb Ethernet/ Intel dual 10Gb Ethernet, 256 Mb Flash ROM, UEFI AMI BIOS, EEB


ASUS PRO WS WRX90E-SAGE SE. Processor manufacturer: AMD, Processor socket: Socket sTR5.

Supported memory types: DDR5-SDRAM, Memory slots type: DIMM, Memory channels: Octa-channel.

Supported storage drive interfaces: M.2, SATA III, SlimSAS, Supported storage drive types: HDD & SSD,

RAID levels: 0, 1, 5, 10. USB connector type: USB Type-A, USB Type-C. Ethernet interface type: 10

Gigabit Ethernet, Fast Ethernet, Gigabit Ethernet



Processor		Internal I/O	
Processor manufacturer *	AMD	TPM connector	✓
Processor socket *	Socket sTR5	Rear panel I/O ports	
Memory		USB 2.0 ports quantity *	1
Supported memory types *	DDR5-SDRAM	USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity *	6
Number of memory slots *	8	USB4 Gen 3x2 ports quantity	2
Memory slots type	DIMM	Ethernet LAN (RJ-45) ports *	2
Memory channels	Octa-channel	VGA (D-Sub) ports quantity *	1
ECC	✓	USB connector type	USB Type-A, USB Type-C
Storage controllers		Network	
Supported storage drive types	HDD & SSD	Ethernet LAN	✓
Supported storage drive interfaces *	M.2, SATA III, SlimSAS	Ethernet interface type	10 Gigabit Ethernet, Fast Ethernet, Gigabit Ethernet
Number of HDDs supported	4	Wi-Fi *	✗
Number of storage drives supported	10	Features	
RAID support	✓	Motherboard chipset *	AMD WRX90
RAID levels	0, 1, 5, 10	Audio chip	Realtek ALC1220P
Internal I/O		Component for *	Workstation
USB 2.0 connectors *	2	Motherboard form factor *	EEB
USB 3.2 Gen 1 (3.1 Gen 1) connectors *	1	Motherboard chipset family *	AMD
USB 3.2 Gen 2x2 connectors	1	Windows operating systems supported	Windows 10 x64, Windows 11
Number of SATA III connectors *	4	Expansion slots	
Front panel audio connector	✓	PCI Express x16 (Gen 5.x) slots	7
ATX Power connector (24-pin)	✓	Number of M.2 (M) slots	4
CPU fan connector	✓	BIOS	
Number of chassis fan connectors	5	BIOS type *	UEFI AMI
Chassis intrusion connector	✓	BIOS memory size	256 Mbit
EPS power connector (8-pin)	✓	Clear CMOS button	✓
Number of COM connectors	1	Weight & dimensions	
		Width	305 mm

Weight & dimensions	
Depth	330 mm
Other features	
Mini DisplayPorts quantity	2



4711387441145

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.

Publication date: 07-MAY-2024. Prints or copies of Information are only valid on the printed Publication date